
Chapter 10—Reviewing and clearing upgrade information

Introduction

This chapter describes how to use the Review Upgrade Information and Clear Upgrade Information options.

These options provide a means of reviewing the upgrade information that was entered and, if required, a means of clearing the upgrade information from the Software Installation Program.

How to review and clear upgrade information

Summary of steps

The steps to review and clear upgrade information are summarized in the following list. They consist of:

- Checking to make sure the Software Delivery (PCMCIA) card is installed.
- Selecting the Utilities menu.
- Selecting Review Upgrade Information option.
- Selecting Clear Upgrade Information option (if required).

Reviewing and clearing upgrade information

The following procedure describes how to review and, if desired, clear the upgrade information.

Review and Clear Upgrade Information Procedure

Step	Action						
1	If not previously done, install the Software Delivery card in the socket in the faceplate of the NTDK20 Small System Controller (SSC) card. Note: This Software Delivery card must be the same one that was used to upgrade this Option 11C. It must not have been used to upgrade a subsequent Option 11C because the Security ID will no longer match and the “undo” function will fail. To install the Software Delivery card: Insert the Software Delivery card in slot A in the PCMCIA socket located in the faceplate of the NTDK20 Small System Controller (SSC) card. Gently press on the Software Delivery card until it is firmly seated.						
2	Select the method of invoking the Software Installation Program. There are two methods of invoking the Software Installation Program: - By using the UPGRADE command in Overlay 143 —or— - By pressing the ‘control’ and ‘I’ keys on the keyboard when prompted after the Software Delivery card is installed. <table> <tr> <th>If</th><th>Do</th></tr> <tr> <td>you wish to invoke the program using Overlay 143</td><td>Step 3</td></tr> <tr> <td>you wish to invoke the program when prompted</td><td>Step 4</td></tr> </table>	If	Do	you wish to invoke the program using Overlay 143	Step 3	you wish to invoke the program when prompted	Step 4
If	Do						
you wish to invoke the program using Overlay 143	Step 3						
you wish to invoke the program when prompted	Step 4						
3	Invoke the Software Installation Program using Overlay 143. Note: Perform this step only when using the Overlay 143 to invoke the Software Installation Program. To invoke the program during a SYSLOAD, skip this step and do Step 4. Login to the system by entering LOGI<cr> then proceed with the following: Note: The response to PASS? is unique to each system. The response shown below is an example. —continued—						

Review and Clear Upgrade Information Procedure (Continued)

Step	Action	Response
	Prompt	
	PASS?	0000<cr>
	.	LD 143<cr>
		UPGRADE<cr>
	If	Do
	SOFTWARE INSTALLATION PROGRAM message appears	Step 5
	SOFTWARE INSTALLATION PROGRAM message does not appear	Repeat Step 3 (this step) and make sure correct information is entered
4	Invoke the Software Installation Program when prompted.	
	Note: Perform this step only when invoking the Software Installation Program when prompted after the Software Delivery card is installed. To invoke the program using Overlay 143, disregard this step and do Step 3 instead.	
	Invoke a system reload (SYSLOAD) by setting the circuit breaker on the front of the power supply in the main cabinet to OFF then to ON.	
	Note: When the FIVE SECONDS TO ENTER CONTROL-I TO INVOKE SOFTWARE INSTALLATION PROGRAM message appears a response must be entered within 5 seconds to invoke the Installer Setup Program.	
	During SYSLOAD, the following prompt will appear:	
	Prompt	Response
	FIVE SECONDS TO ENTER CONTROL-I TO INVOKE SOFTWARE INSTALLATION PROGRAM	Press and hold 'control' key and press 'I'
—continued—		

Review and Clear Upgrade Information Procedure (Continued)

Step	Action				
5	Select Utilities from the Main Menu. Software Installation Main Menu 1. New System Installation or Option 11/11E Upgrade - From Software Daughterboard 2. System Upgrade 3. Utilities 4. New System Installation - From Software Delivery Card [q]uit, [h]elp or [?], <cr> - redisplay <table> <tr> <th>Prompt</th><th>Response</th></tr> <tr> <td>Enter Selection:</td><td>3<cr></td></tr> </table>	Prompt	Response	Enter Selection:	3<cr>
Prompt	Response				
Enter Selection:	3<cr>				
6	Select the Review or Clear option from the Utilities Menu. Utilities Menu: 1. Restore Backed Up database 2. Archive Customer defined databases 3. Install Archived database 4. Review Upgrade Information 5. Clear Upgrade Information 6. Undo Installation 7. Flash Boot ROM Utilities 8. Current Installation Summary [q]uit, <cr>current menu, [m]ain, [p]revious menu, <table> <tr> <th>Prompt</th><th>Response</th></tr> <tr> <td>Enter Selection:</td><td> 4<cr> (Review Upgrade Information) 5<cr> (Clear Upgrade Information) </td></tr> </table>	Prompt	Response	Enter Selection:	4<cr> (Review Upgrade Information) 5<cr> (Clear Upgrade Information)
Prompt	Response				
Enter Selection:	4<cr> (Review Upgrade Information) 5<cr> (Clear Upgrade Information)				
—continued—					

Review and Clear Upgrade Information Procedure (Continued)

Step	Action						
	<table> <tr> <th>If</th><th>Do</th></tr> <tr> <td>response was 4<cr></td><td>Step 7</td></tr> <tr> <td>response was 5<cr></td><td>Step 8</td></tr> </table>	If	Do	response was 4<cr>	Step 7	response was 5<cr>	Step 8
If	Do						
response was 4<cr>	Step 7						
response was 5<cr>	Step 8						
7	Review summary of upgrade information.						
	<pre> Software Upgrade Summary: Security ID : 12345678 Aux ID : 12345678 Database : Retain current NEW S/W Release : 2308b ISM Parameters : NEW TSN : 1000 AGNT : 1000 ACDN : 0100 AST : 0100 DSL : 0100 LTID : 0000 MOPT : 0000 </pre> Return to Step 6						
	—continued—						

Review and Clear Upgrade Information Procedure (Continued)

Step	Action										
8	Review and clear or retain upgrade information. Software Upgrade Summary: Security ID : 12345678 Aux ID : 12345678 Database : Retain current NEW S/W Release : 2308b ISM Parameters NEW TSN : 1000 AGNT : 1000 ACDN : 0100 AST : 0100 DSL : 0100 LTID : 0000 MOPT : 0000 <table> <tr> <th>Prompt</th><th>Response</th></tr> <tr> <td>Do you wish to clear the Upgrade information?</td><td> y<cr> (yes) n<cr> (no) a<cr> (abort, return to main menu) </td></tr> <tr> <th>If</th><th>Do</th></tr> <tr> <td>response was y</td><td>—End—</td></tr> <tr> <td>response was n</td><td>Step 5</td></tr> </table> —End—	Prompt	Response	Do you wish to clear the Upgrade information?	y<cr> (yes) n<cr> (no) a<cr> (abort, return to main menu)	If	Do	response was y	—End—	response was n	Step 5
Prompt	Response										
Do you wish to clear the Upgrade information?	y<cr> (yes) n<cr> (no) a<cr> (abort, return to main menu)										
If	Do										
response was y	—End—										
response was n	Step 5										